

# 6 ZONES MIXER AMPLIFIER WITH AUDIO SOURCE AND TIMER

Mixer Amplifier



## DESCRIPTION

The Integrated Mixer Amplifier is a 6 zones mix amplifier integrated with the functions of U disk, SD card, tuner, radio, Blue tooth, zones and timer. With various functions, including song files playing, radio, schedule time etc. Touch screen control, all graphical interface, the operation is very simple and user-friendly. The device can meet the requirements of the users and can be widely applied.

## FEATURES

- ⊕ Support USB/SD/MP3/AM & FM/Bluetooth/schedule player
- ⊕ 6 zones output with separated switch control
- ⊕ 4.3" TFT capacitance touch screen.
- ⊕ Touch and button-pressing control. Can operate with physical buttons when touch screen is broken.
- ⊕ Built-in 4G MP3 program memory.
- ⊕ Built-in radio; it can be manually / automatically searched and can store 40 radio channels.
- ⊕ Built-in Bluetooth receiver module.
- ⊕ 1 AUX, 1 Mic input, 1 AUX output.
- ⊕ Separate volume control for MP3/FM/Bluetooth, AUX, Mic inputs
- ⊕ With Bass & Treble sound effect adjustment, with Master Volume control for all output
- ⊕ Weekly programmable schedule set with more than 100 daily programmable schedule points. It can remember where it ends abnormally when it restarts. More than 8 different plans for schedule set.
- ⊕ Two kinds of control modes — schedule and manual.
- ⊕ Mic input with muting priority
- ⊕ Power output: 100V

Specifications					
Model	NVS-90060156MA	NVS-90070256MA	NVS-90080356MA	NVS-90090456MA	NVS-90100656MA
Rate power	150W	250W	350W	450W	650W
Speaker Outputs	100V				
Harmonic Distortion	<0.5% (1kHz , 1/3 rate power)				
AUX Output	100Ω, 1V ( 0dBV )				
Input	Mic: 600Ω; 8mV (±10%) Line: 10kΩ, 300mV (±10%), unbalanced				
Line Freq.response	50Hz-20kHz (±3dB)				
Mic Freq.response	40Hz-16kHz (±3dB)				
Harmonic distortion	< 0.5% (1kHz , 1/3 rated power)				
S/N Ratio	Mic: 70dB Line: 80dB				
Tone	Bass: ±10dB (100Hz) Treble: ±10dB (10kHz)				
Protection	AC fuse, DC output protection, overload protection.				
Power Supply	AC220-240V/50-60Hz				
Power Consumption	220W	350W	450W	560W	800W
Dimension	418x338x88mm				

NVS-90060156/90070256/90080356/90090456/90100656MA

# 6 ZONES MIXER AMPLIFIER WITH AUDIO SOURCE AND TIMER

## FRONT PANEL



- |  |  |
|--|--|
| <ol style="list-style-type: none"> <li>1. Power switch</li> <li>2. Power indicator</li> <li>3. USB port</li> <li>4. Often-used function selection buttons</li> <li>5. Display screen</li> <li>6. MP3/FM/Bluetooth volume control button</li> </ol> | <ol style="list-style-type: none"> <li>7. Aux volume control button</li> <li>8. Microphone volume control button</li> <li>9. Microphone interface</li> <li>10. Button for all volume together</li> <li>11. Treble button</li> <li>12. Bass button</li> </ol> |
|--|--|

## REAR PANEL



- |   |  |
|---|--|
| <ol style="list-style-type: none"> <li>1. AM/FM antenna</li> <li>2. Aux input interface</li> <li>3. Aux output interface</li> <li>4. SD card slot</li> <li>5. Zone output terminal</li> </ol> | <ol style="list-style-type: none"> <li>6. Power wire</li> <li>7. Fan cooling window</li> <li>8. Bluetooth antenna</li> <li>9. Individually output</li> <li>10. Amplifier fuse</li> </ol> |
|---|--|

## ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-90060156MA	70V 150W 6 Zones Mixer Amplifier with Audio Source and Timer	1 No.
NVS-90070256MA	100V 250W 6 Zones Mixer Amplifier with Audio Source and Timer	1 No.
NVS-90080356MA	100V 350W 6 Zones Mixer Amplifier with Audio Source and Timer	1 No.
NVS-90090456MA	100V 450W 6 Zones Mixer Amplifier with Audio Source and Timer	1 No.
NVS-90100656MA	100V 650W 6 Zones Mixer Amplifier with Audio Source and Timer	1 No.

## PACKING INFORMATION

Part Number	Packing Mode	Dimensions(mm)
NVS-90060156MA	Carton Box	418x338x88
NVS-90070256MA	Carton Box	418x338x88
NVS-90080356MA	Carton Box	418x338x88
NVS-90090456MA	Carton Box	418x338x88
NVS-90100656MA	Carton Box	418x338x88