

STEREO MIXER PRE- AMPLIFIER

N-114S04



FEATURES

- ◆ Standard machine cabinet type 1 U height design, black aluminum oxide draw bench panel.
- ◆ 4 MIC/LINE XLR balanced inputs, providing 48V phantom power switch.
- ◆ 4 AUX accessory unbalanced inputs, there are 2 RCA in each channel, and one of them is on the panel.
- ◆ Each channel is equipped with volume control and tone control.
- ◆ Signal/peak value LED light monitors the input level of every channel.
- ◆ MIC/LINE1, MIC/LINE2 internally installed low cut.
- ◆ Each input channel can be assigned to output channel freely through jumper.
- ◆ The panel provides one channel of MIC/LIN input in addition, parallel connected with MIC/LINE1.
- ◆ MIC1/MIC2 priority control, and adjustable threshold value.
- ◆ 4 XLR balanced outputs, in parallel connection with 2 channels of RCA unbalanced outputs.
- ◆ 4 RJ45 trunk balanced inputs, whose volume is adjustable, and can be mixed correspondingly into 4 channel XLR outputs.
- ◆ 4s of RJ45 trunk balanced outputs mixed signal.
- ◆ Output level indicate.
- ◆ External mute controls all channels.
- ◆ Switching power supply provides electricity.

SPECIFICATIONS

Model	N-114S04
Input Sensitivity/Impedance	
1-4MIC/ Line	±2.5mV/5KΩ balanced, ±250mV/5KΩ balanced
1-4AUX RCA In	400mV/5KΩ unbalanced
Output Level/Impedance	
Master 1,2,3,4	1V/600Ω balance (MAX:± 7.75V)
AUX	1V/10KΩ unbalanced (MAX:7.75V)
Tone	Bass: ±15dB at 100Hz, Treble: ±15dB at 10KHz
Low Cut	200Hz / 12dB per octave slope
Frequency Response	
Less Than	
S/N Ratio	-1dB(20Hz~20KHz)
MIC	
Line	> 60dB
THD	> 75dB

STEREO MIXER PRE- AMPLIFIER

N-114S04

SPECIFICATIONS

Model	N-114S04
MIC	
Line	< 0.05%
Cross-talk	> 0.03%
MIC	> 60dB
Line	> 75dB
Power Consumption Power	20W
Power Supply	~110V-230V 50/60Hz
Dimensions	484x209x44mm
Weight	3.9Kg

ORDERING INFORMATION

Part Number	Description	Standard Quantity
N-114S04	Stereo Mixer Pre- Amplifier	1 No.

PACKING INFORMATION

Part Number	Packing Mode	Gross Weight(kg)	Dimensions(mm)
N-114S04	Carton Box	3.9	484x200x44